

COPPER ROUND FERRULES


Available from Code		2 to 8			
Ferrule No.	Wire rope diameter -Ø in mm Fibre core and IWRC		Swaging dies no.	Diameter after swaging	
	min.	max		mm	
2	1,6	2,0	2	4	
3	2,7	3,1	3	6	
4	3,7	4,1	4	8	
5	4,7	5,1	5	10	
6	5,7	6,2	6	12	
6,5	6,3	6,6	6,5	13	
7	6,7	7,2	7	14	
8	7,8	8,2	8	16	

We reserve the right to amend technical data